

AMENDMENTS TO THE CLAIMS

This listing of claims will replace all prior versions and listings of claims in the application:

Listing of Claims:

1. (Previously presented) A method for calibrating an electromagnetic logging tool having a plurality of antennas disposed thereon with at least one antenna having its axis at an angle with respect to the axis of the tool, each antenna being configured to transmit and/or receive electromagnetic energy, comprising the steps of:
 - (a) disposing a test loop about the electromagnetic logging tool such that the axis of the tool and a plane on which the test loop lies form a tilt angle that is between about 0 and 90 degrees;
 - (b) measuring a signal induced in one of said antennas when another of said antennas is energized, the induced signal being affected by the test loop;
 - (c) determining a correction for the induced signal, including producing a corrected signal and comparing the corrected signal with a calculated signal based on a model including the electromagnetic logging tool and the test loop; and
 - (d) further comprising deriving a gain or phase factor by comparing the corrected signal with the calculated signal.
2. (Previously presented) The method of claim 1, wherein step (c) includes applying to the induced signal a correction selected from a group consisting of a sonde error correction and temperature correction.
3. (Canceled)
4. (Canceled)

5. (Original) The method of claim 1, further comprising:

altering a position of the test loop about the electromagnetic logging tool and repeating steps (b) to (c).
6. (Original) The method of claim 1, further comprising deriving calibration coefficients for at least one of the antennas.
7. (Original) The method of claim 1, wherein the tilt angle is 45 degrees.
8. (Original) The method of claim 1, wherein at least one of the antennas comprises a plurality of coils having mutually orthogonal axes.
9. (Original) The method of claim 1, wherein at least one of the antennas comprises a plurality of coils having non-parallel axes.
10. (Original) The method of claim 1, wherein the at least one antenna having its axis at an angle comprises a transverse antenna.
11. (Canceled)
12. (Canceled)
13. (Previously presented) The method of claim 1, further comprising multiplying the corrected signal by gain or phase factors.
14. (Canceled)
15. (Previously presented) The method of claim 1, wherein step (c) includes determining a maximum or minimum value associated with the measured signal.
16. (Original) The method of claim 1, wherein step (b) includes rotating the test loop about the axis of the tool.
17. (Original) The method of claim 1, wherein step (b) includes displacing the test loop off the axis of the tool.

18. (Currently amended) A system for calibrating an electromagnetic logging tool, comprising;

a plurality of antennas disposed on the logging tool with at least one antenna having its axis at an angle with respect to the axis of the tool, each antenna being configured to transmit and/or receive electromagnetic energy;

a test loop positionable about the logging tool such that the axis of the tool and a plane on which the test loop lies form a tilt angle that is between about 0 and 90 degrees; and

a processor configured to calculate a correction for a measured signal induced in one of ~~said the~~ plurality of antennas by another of ~~said the plurality of~~ antennas, the induced signal being affected by the test loop, wherein the processor is further configured to calculate ~~said the~~ correction using a second measured signal induced at ~~said the one of the plurality of~~ antennas without any effect associated with the test loop.

19. (Original) The system of claim 18, wherein the tilt angle is 45 degrees.

20. (Original) The system of claim 18, wherein at least one of the antennas comprises a plurality of coils having mutually orthogonal axes.

21. (Original) The system of claim 18, wherein at least one of the antennas comprises a plurality of coils having non-parallel axes.

22. (Original) The system of claim 18, wherein the at least one antenna having its axis at an angle comprises a transverse antenna.

23. (Original) The system of claim 18, wherein the processor is [[adapted]] configured to apply to the induced signal a correction selected from the group consisting of a sonde error correction and temperature correction.

24. (Canceled)

25. (Previously presented) The system of claim 18 wherein the test loop comprises a conductive loop having means for selective opening or closing of said loop.

26. (Previously presented) The system of claim 18, wherein the processor is configured to produce a corrected signal and to compare the corrected signal with a calculated signal.

27. (Previously presented) The system of claim 26, wherein the processor is configured to derive a gain or phase factor by comparing the corrected signal with the calculated signal.

28. (Previously presented) The system of claim 26, wherein the processor is configured to multiply the corrected signal by gain or phase factors.

29. (Original) The system of claim 26, wherein the calculated signal is based on a model including the electromagnetic logging tool and the test loop.

30. (Previously presented) The system of claim 18, wherein the processor is configured to derive calibration coefficients for at least one of the antennas.

31. (Original) The system of claim 18, wherein the calculation for the induced signal correction includes determining a maximum or minimum value associated with the induced signal.

32. (Previously presented) The system of claim 18, wherein the test loop is positionable for rotation about the axis of the tool.

33. (Previously presented) The system of claim 18, wherein the test loop is configured for displacement off the axis of the tool.

34. (Previously presented) A system for calibrating an electromagnetic logging tool having a plurality of antennas disposed thereon with at least one antenna having its axis at an angle with respect to the axis of the tool, each antenna being configured to transmit and/or receive electromagnetic energy, comprising:

a test loop positionable about the logging tool such that the axis of the tool and a plane on which the test loop lies form a tilt angle that is between about 0 and 90 degrees;

a computer connectible to the electromagnetic logging tool, wherein the computer is configured to process a program with instructions to perform:

energizing a first antenna on the tool in the presence of the test loop;

measuring an induced signal at a second antenna on the tool; and

determining a correction for the induced signal, wherein determining the correction for the induced signal includes using a signal induced at the second antenna with the test loop open.

35. (Original) The system of claim 34, wherein at least one of the antennas comprises a plurality of coils having mutually orthogonal axes.

36. (Original) The system of claim 34, wherein at least one of the antennas comprises a plurality of coils having non-parallel axes.

37. (Canceled)

38. (Previously presented) The system of claim 34, wherein the test loop comprises a conductive loop having means for selective opening or closing of said loop.

39. (Canceled)

40. (Original) The system of claim 34, the program including further instructions to determine a corrected signal and to compare the corrected signal with a calculated signal.

41. (Original) The system of claim 34, wherein determining the correction for the induced signal includes determining a maximum or minimum value associated with the induced signal.

42. (Previously presented) The system of claim 34, wherein the test loop is rotatable about the axis of the tool.

43. (Previously presented) The system of claim 34, wherein the test loop is configured for displacement off the axis of the tool.